

PARTS LIST AND DESCRIPTIONS (Continued)

TRANSFORMER (POWER)

ITEM No.	RATING				REPLACEMENT DATA		
	PRI.	SEC. 1	SEC. 2	SEC. 3	Bell Sound PART No.	STANCOR PART No.	CHICAGO PART No.
T1	117VAC ③ .63A	640VCT 110ADC	5VAC ③ 2A	6.3VAC ③ 2A	B-20166	P-3153	PV-120 ①

① Drill new mounting holes

TRANSFORMER (AUDIO OUTPUT)

ITEM No.	RATING				REPLACEMENT DATA		
	IMPEDANCE PRI.	DC RES. PRI.	SEC.	SEC.	Bell Sound PART No.	STANCOR PART No.	CHICAGO PART No.
T2	6.3KΩ 16Ω tap @ 80.4Ω	410Ω 1.18Ω CT 82Ω			B-20229	A-3880	A-3016

FUSES

ITEM No.	TYPE	RATING	REPLACEMENT DATA			
			Bell Sound PART No.	FUSE	HOLDER	BUSS PART No.
M1	3AG	2A typ. 250V.		312002 (3AG-2A)	342001	HOLDER

MISCELLANEOUS

ITEM No.	PART NAME	Bell Sound PART No.	NOTES
M2	Switch		Function Selector

CHASSIS—BOTTOM VIEW

